

Product: **Wire Tracker Kit**

Images: for more images -
[view product page on our site](#)



SKU: HP-TRACK-806R

Description: Network Wire Tracker handy support Trace telephone wire & LAN cable.

Main functions:

Check and find the needed cables among so many cables in one time.

Continuity test – wiremap for Lan cables.

Diagnose the breakage, open, short, cross.

Visible indication: pin-to-pin cable map for individual cable (not by pairs).

Transmitter with RJ11 connector and pair of alligator clips.

Low Voltage alarm function.

Earphone permits use in noisy environments.

LED light assists use in dark corners.

Specifications: **NF-806 Transmitter specifications**

Tone frequency:	90-1000kHz
Max. distance of transmission:	Up to 2 kilometers
Max. working current:	Less than 10mA
Volume Regulate Function:	Audio volume level control
Tone mode:	2 Tones adjustable
Compatible connectors:	RJ45, RJ11, adaptor
Max. signal voltage:	8Vp-p
LED lights display:	Wiremap, tone, tracing
Voltage protection:	AC 60V/DC 42V
Battery Type:	DC9.0V (NEDA 1604/6F22) x 1pc
Dimensions (cm):	L 15 × W 3.7 × D 2
NF-806 Receiver specifications	
Frequency:	200kHz
The Max. working current:	Less than 30mA
Earphone jack:	1
Battery Type:	DC9.0V (NEDA 1604/6F22) x1pc
Dimensions (cm):	L 12.2 × W 4.5 × D 2.3

Attention:

Do not connected higt voltage lines to avoid buring out the machine
Put into the right place to avoid hurting other, because of the sharp part
Connected the cable to the right port
Read the user manual before use it

included:

- NF-806R Transmitter x1
- NF-806R Receiver x 1
- RJ45 adaptor cable x 1
- Earphone x 1
- DC9.0V Battery x 2
- Case x 1
- User manual

